



The new Panda 4000s

The next generation of super silent generators - for more power onboard



- High starting capacity...**
 Perfect for running a diving compressor or air conditioner
- 230 V / 50 Hz...**
 For your complete on-board power system
- Extremely compact and light...**
 More room for other things
- Super silent sound insulation capsule...**
 You can relax while the generator runs
- Innovative Design.**
 Easy to install and maintain
- Integrated fuel pump and voltage stability...**
 Improved performance



Generator

Type		Panda 4000s PMS
Dimensions (LxWxH)	[mm]	575 x 365 x 550 (LxWxH)
Weight	[kg]	97
Sound level (7m / 3m / 1m)	[dB]	54 / 64 / 69
Cooling System		Dual circuit version - freshwater cooling via heat exchanger Single circuit version- seawater cooling

Performance

Nominal Output	[kW]	3.8 kW
Continuous Output	[kW]	3.5 kW
Voltage Stability	[%]	230 V \pm 5%
Frequency Stability	[%]	50 Hz \pm 2Hz

Control

Starter System		Electric Start
Remote Control Panel		Panda P4 Control

Engine

Engine Manufacturer		Farymann
Engine Type		18W430
Engine Displacement	[ccm]	298
Speed	[rpm]	3000

Disclaimer: The information contained here is to the best of our knowledge accurate at the date of publication. All products are subject to continuous development and Fischer Panda GmbH reserves the right to alter technical specifications without prior notice.



Fischer Panda

Fischer Panda GmbH

Otto-Hahn-Str. 32-34 • 33104 Paderborn, Germany

Telephone +49 (0) 52 54 / 9202-0 • Telefax +49 (0) 52 54 / 9202-550

E-Mail: info@fischerpanda.de

www.fischerpanda.net

Contact your Fischer Panda distributor for more information: